

MULTIMETER
YX-360 TRE-B



DC Current

Resistance

AC / DC Voltage

Diode

Temp

Continuity

Low Battery Indication

Over Range Display

600V

- FEATURES :**
- ✓ ANALOG MULTIMETER WITH MIRROR SCALE
 - ✓ INBUILT BUZZER AND LED
 - ✓ 0Ω ADJUSTABLE KNOB
 - ✓ TRANSISTOR TEST hFE
 - ✓ DIODE TEST
 - ✓ ICEO (LEAKAGE CURRENT) TEST

DC VOLTAGE

RANGE	SENSITIVITY	ACCURACY
0.1 V	20KΩ/V	3 (for 1000V) 5
0.5 V		
2.5 V		
10 V		
50 V		
250 V		
1000 V		

DC CURRENT

RANGE	VOLTE DROP	ACCURACY
50μA	250mV	FSD : 3 (10A:5)
2.5 mA		
25mA		
0.25A		
10A		

AC VOLTAGE

RANGE	SENSITIVITY	ACCURACY
10 V	9KΩ/V	4 (for 1000V) 5
50 V		
250 V		
1000 V		

RESISTANCE

RANGE	MIDSCALE	ACCURACY
x1-0.2Ω~2KΩ	20Ω	FSD : 3
x10-2Ω~20KΩ	200Ω	
x100-20Ω~200KΩ	2KΩ	
x1K-200Ω~2MΩ	20KΩ	
x10K-2KΩ~20MΩ	200KΩ	

POWER

AAA 1.5V x 2	
9V (6F22) x 1	
Dimension	: H148 x W100 x D35 mm
Weight	: Approx. 280 Gms.
Accessories	: Test leads, User Manual & Battery.
Qty	: 40 Pcs. in a Box.

- hFE 0-1000 (with connector extra)
- During hFE test :
Range select x 10 (15mA) for small transistor,
1 (150mA) for big transistor,
- Iceo 150uA-15mA-150mA